


PCB Cleaner



Technical Data

AMBERSIL PCB CLEANER is a solvent based cleaner for use on printed circuit boards (PCB's) to efficiently remove light soiling such as thin oils, thermal paste, light flux residue, ink, solvent soluble coatings and grime. PCB Cleaner has excellent material compatibility and is specifically formulated for use on delicate electronics. It evaporates quickly, leaving a clean, dry, residue-free surface.

When used in electronic servicing, PCB Cleaner allows the engineer to remove any contaminants or residues which may have built-up on the board prior to diagnostic testing, reducing the risk of current seepage, arcing or false readings being generated. After servicing, PCB Cleaner should be applied to provide a clean surface for the re-application of the conformal coating (if required) and re-installation.

APPLICATIONS

- Light cleaning and degreasing of printed circuit boards
- Removal of grime from electrical components
- Cleaning contact points on wires and terminals
- Removal of contaminants and post-processing residues
- Efficient cleaning as part of scheduled maintenance




PART NUMBER:
6130004010

TECHNICAL DATA

Appearance	:	Clear, colourless liquid
Odour	:	Hydrocarbon solvent
SG @ 25°C	:	0.67
Pressure @ 25°C	:	3.0 Bar
Discharge rate	:	1.1 g/sec
Solubility	:	Miscible with most organic solvents
Packaging	:	400 ml aerosol

STORAGE

The product may be stored at normal ambient temperatures and has a shelf life of not less than 72 months with correct storage. Aerosols should always be stored below 50°C, away from direct heat and naked flame.



HEALTH AND SAFETY

Health and Safety sheet available separately.

TECHNICAL SERVICE

CRC Industries UK Ltd provides a technical support service and maintains a constant programme of research and development. We are able to assist customers by specific product development to meet particular requirements.

MISREPRESENTATION ACT 1967 TRADE DESCRIPTIONS ACT 1968

The information given in this publication is based on our experience and reports from customers. There are many factors outside our control and knowledge which affect the use and performance of our products and for which reason no warranty is given, express or implied. Users should make their own tests to determine the applicability of such information or the suitability of any products for their own particular purposes. Statements concerning the use of the products described herein are not to be construed as recommending the infringement of any patent and no liability for infringement arising out of any such use is to be assumed.